

Technical Documentation of (EC) No 1275/2008

Entry No.	Product type	Projector
1	Networked equipment type	Other networked equipment
2	Manufacturer name, address	Acer Italy srl Viale De Gasperi 88/A 20017 Mazzo di Rho (MI) Italy
3	Product model number	F7200; F7600
4	Year of manufacture	2016
5	For products with a display unit or light source, the total content of mercury is	32 mg
6	The number and type of network ports with the exception of wireless network ports; in particular it shall be declared if the same physical network port accommodates two or more types of network ports	Number: 1 Type: RJ45
7	Where these ports are located on the equipment	Rear
8	The number and type of wireless network ports; in particular it shall be declared if the same physical network port accommodates two or more types of network ports	Number: 0 Type: not applicable
9	Whether all network ports are deactivated before delivery	No
10	Power consumption of standby mode	0.37 Watt
11	Power consumption of off mode	Not applicable
12	Power consumption in networked standby if all wired network ports are connected and all wireless network ports are activated	1.51 Watt
13	Power consumption of configuration with highest networked standby power consumption. Only required if it is not possible to test the configuration with all wired network ports connected and all wireless network ports activated	Not applicable
14	For each type of network port, the (maximum) power consumption of the condition providing networked standby, if only this port is used for remote activation	1.51 Watt
15	The default time after which the power management function, or similar function, has switched the equipment into standby mode	5 mins

16	The default time after which the power management function, or similar function, has switched the equipment into off mode	Not applicable
17	The default time after which the power management function, or similar function, has switched the equipment into another condition which does not exceed the applicable power consumption requirements for off mode and/or standby mode when the equipment is connected to the mains power source.	5 mins
18	For each type of network port, the default time after which the power management function, or similar function, has switched the equipment into the condition providing networked standby	5 mins
19	For each type of network port, the trigger used to reactivate the equipment	1. Open web browser (e.g. Internet Explorer) 2. Key in OSD IP address 3. Push power button on web browser
20	For each type of network port, the (maximum) performance specifications	100M bit/s.
21	For each type of network port, the communication protocol used by the equipment	TCPIP / IPv4
22	Guidance on how to activate and deactivate wireless network ports	Not applicable
23	Equipment characteristics relevant for assessing conformity with the requirements set out in point 2(c) and/or 2(d) and/or 3(b)	2(c)- The product has "standby mode", which is compliant with 2 (c) requirement 2(d)- The product will automatically enter "standby mode" after 5 minutes of inactivity, which is compliant with 2 (d) requirement 3(b)- The product will enter "networked standby mode" after 5 minutes of networked inactivity, which is compliant with 3 (b) requirement.
24	Technical justification that the requirements set out in points 2(c) and/or 2(d) and/or 3(b), are inappropriate for the intended use of equipment	Not applicable
25	Measurement methodology for standby mode	According to IEC 62301 & EN50564.
26	Measurement methodology for off mode	Not applicable
27	Measurement methodology for the condition providing networked standby	According to IEC 62301 & EN50564.
28	Description of how standby mode was selected or programmed	Method 1- Power on the product, keep it in "no signal input" state, and then it will automatically enter "standby mode" in 5 minutes Method 2- Power on the product, open OSD window > Page" Installation II" > Advanced > item "Low power mode" > On .
29	Description of how off mode was selected or programmed	Not applicable

30	Description of how the condition providing networked standby was selected or programmed	Power on the product, open OSD window > Page" Installation II" > Advanced > item "Low power mode" > "ON by LAN" .
31	Sequence of steps for achieving a stable condition with respect to power demand	When the product enter a specific mode (e.g. standby mode), wait for 5 minutes, and then its power consumption will enter stable condition.
32	Sequence of events leading to the condition where the equipment automatically changes to standby mode	Power on the product, keep it in "no signal input" state, and then it will automatically enter "standby mode" in 5 minutes.
33	Sequence of events leading to the condition where the equipment automatically changes to off mode	Not applicable
34	Sequence of events leading to the condition where the equipment automatically changes to the condition providing networked standby	Power on the product, keep it in "no networked-signal input" state, and then it will automatically enter "standby mode" in 5 minutes.
35	Notes regarding the operation of the equipment	The networked-signal to the product is generated via desktop/notebook's TCP/IP/ IPv4 protocol. A/V signal and content is generated via Signal Generator Chroma 2235
36	Test parameter for ambient temperature	25 °C
37	Test parameter for test voltage	230 V
38	Test parameter for frequency	50 Hz
39	Test parameter for total harmonic distortion of the electricity supply system	10%
40	Test parameter for information and documentation on the instrumentation, set-up and circuits used for electrical testing	1. Chroma AC source 61504 2. Powermeter Chroma 66202