

Technical Documentation of (EC) No 1275/2008

Product type	Projector
Manufacturer name, address	Acer Italy s.r.l, Via Lepetit, 40, 20020 Lainate (MI) Italy
Product model number	P6500, P6600
Year of manufacture	2015
Standby mode power consumption	0.49 Watt
Off mode power consumption	Not applicable
Networked standby mode power consumption	2.87 Watt
Power consumption of the product in networked standby if all wired network ports are connected and all wireless network ports are activated	Not applicable
For products with an display or light source, the total content of mercury is	45 mg
The default time after which the power management function, or similar function, has switched the equipment into standby mode	15 minutes
The default time after which the power management function, or similar function, has switched the equipment into off mode	Not applicable
The default time after which the power management function, or similar function, has switched the equipment into another condition which does not exceed the applicable power consumption requirements for off mode and/or standby mode when the equipment is connected to the mains power source.	15 minutes
The default time after which the power management function, or similar function, has switched the equipment into networked standby mode	15 minutes
Technical justification that the requirements set out in points 2(c) and/or 2(d) and/or 3(b), are inappropriate for the intended use of equipment	Not applicable
Measurement methodology for standby mode	According to IEC 62301:2011 and EN 50564:2011
Measurement methodology for off mode	Not Applicable

Measurement methodology for networked standby mode	According to IEC 62301 and EN 50564
Description of how standby mode was selected or programmed	1. Plug in power cord, but no input source. 2. Will show the status by LED indicator. (LED will show in steady RED color)
Description of how off mode was selected or programmed	Not applicable
Sequence of steps for achieving a stable condition with respect to power demand	Allow the Test Unit to warm up (Power On) for a minimum of 20 minutes
Sequence of events leading to the condition where the equipment automatically changes to standby mode	1. To disable the network setting in OSD . 2. While system is on and with no signal after 15min, will automatically switch to standby mode, or 3. While Security is on and no entering password, system will automatically switch to standby mode.
Sequence of events leading to the condition where the equipment automatically changes to off mode	Not applicable
Sequence of events leading to the condition where the equipment automatically changes to networked standby mode	1. To enable the network setting in OSD . 2. While system is on and with no signal after 15min, will automatically switch to standby mode, or 3. While Security is on and no entering password, system will automatically switch to standby mode.
Notes regarding the operation of the equipment	Setting projector by OSD definition
Guidance on how to activate and deactivate wireless network ports	Not applicable
Test parameter for ambient temperature	25 °C
Test parameter for test voltage	230 V
Test parameter for frequency	50 Hz
Test parameter for total harmonic distortion of the electricity supply system	0.03 %

<p>Test parameter for information and documentation on the instrumentation, set-up and circuits used for electrical testing</p>	<ol style="list-style-type: none"> 1. Equipment setup: <ol style="list-style-type: none"> 1.1 AC Power Source: EXTECH / 6210 1.2 Pattern Generator: QuantumData 802B 1.3 Power-Meter: YOKOGAWA WT210 1.4 Test unit: P6200 2. Test Condition: <ol style="list-style-type: none"> 2.1 AC Power Source : <ol style="list-style-type: none"> 2.1.1 Input power and frequency: 230Volts (+/-1%) AC, 50Hz (+/-1%) 2.2 Pattern Generator : <ol style="list-style-type: none"> 2.2.1 Display Pattern: Full White 2.2.2 Resolution/ Timing: 1280*800/60Hz 2.2.3 Ambient Temperature: 23 +/-2 °C, 65%
---	---