

Acer BIOS Flash SOP

(For Windows)

Document: SOP

Issue Date: 11/29/2012

Document Revision: v1.5

	APPROVED	CHECKED	PREPARED
BY	Vincent Lu	Seabird Fang	Eleven Luo
DATE	11/29/2012	11/29/2012	11/29/2012

This document contains proprietary and confidential information of Foxconn. All rights and titles hereto remain with Foxconn. The recipient shall keep this document in strict confidence and shall use this document in the manner and solely for purposes expressly agreed to by Foxconn. The recipient shall not disclose or allow access to this document, in whole or in part, by third parties, nor use it for the benefit of the recipient or third parties. The recipient shall not change this document in form and substance by any means, including without limitation, decompile, reproduce, revise, and amend.

[illegible]

Flash System uEFI BIOS SOP for Windows:


1. Open “WIN\win32” folder if using Windows 32bit or Open “WIN\win64” folder if using Windows 64bit.

名称	修改日期	类型	大小
win32	2011/11/9 13:47	文件夹	
win64	2011/11/9 13:47	文件夹	

2. Please double click “Winflash.bat”.

Name	Date modified	Type	Size
AFUWINGUI	7/17/2012 11:43 AM	Application	665 KB
AFUWINGUI	5/23/2011 1:37 AM	Text Document	6 KB
afuwinx64	7/17/2012 11:43 AM	Application	330 KB
AFUWINx64	7/6/2012 3:08 PM	Text Document	3 KB
AMI_Aptio_AFU_User_Guide_NDA	7/6/2012 3:10 PM	PDF File	317 KB
amifldr32.sys	4/20/2012 11:16 AM	System file	13 KB
amifldr64.sys	4/20/2012 11:16 AM	System file	16 KB
readme	7/6/2012 3:08 PM	Text Document	4 KB
readme_afuwin	1/6/2012 5:12 PM	Text Document	1 KB
Winflash	8/22/2012 8:45 PM	Windows Batch File	1 KB


3. Press “Yes” to continue flashing BIOS.




4. Please waiting BIOS update process. Please restart you system after updating BIOS completely.

5. When system restart, please press “Del” to enter BIOS Setup.


6. In Exit page, select “Load Default Settings” and press “Enter” key.




7. Select "Yes" and press "Enter" key.



8. Select "Save & Exit Setup" and press "Enter" key.



9. Select "Yes" and press "Enter" key.



10. Flash BIOS is finished.